

QSO Flow:

| You are: The SEARCH & POUNCE station (You are using N3FJP logging software) | | The other guy is: The RUNNING station station (It doesn't matter how he logs his QSOs.) |
|--|---|---|
| You hear the other guy's CQ or QRZ. Copy his call sign and type it into CALL box | ← | CQ TEST [his call sign] TEST Or, QRZ [his call sign] TEST |
| TAB to send the F2 S&P message. Send his call sign | → | He copies your call sign |
| SPACE BAR to advance your cursor. Copy and enter his exchange into your log. | ← | He sends: Your call sign and his exchange |
| ENTER to send the F3 RUN message and log the QSO. R TU 5NN PA | → | He copies and types your exchange into his log. |
| Hear his acknowledgement, then QSY. Tune up or down the band looking for a new contact. | ← | He acknowledges your exchange by sending R or QSL . He stays on frequency for the next QSO cycle by calling CQ TEST. |

Type CTRL + SHIFT + G (three keys all together) to activate TAB SENDS MESSAGE feature.

Function Buttons Setup – SEARCH & POUNCE Mode:

- F1 CQ TEST [your call sign] TEST (you won't be using this as a S&P)
- F2 [your call sign]
- F3 R TU 5NN PA
- F4 [your call sign] – used for repeats
- F5 TU 5NN PA – used for repeats
- F6 R TU [your call sign] – used for repeats
- F7 AGN
- F8 reserved for double sending your exchange
- F9
- F10
- F11
- F12

If or when you switch between Running and Search & Pounce you must edit your F2 and F3 buttons.

QSO Flow:

| You are: The RUNNING station (You are using N3FJP logging software) | | The other guy is: The SEARCH & POUNCE station (It doesn't matter how he logs his QSOs.) |
|---|---|---|
| CQ TEST [your call sign] TEST Or, QRZ [your call sign] TEST | ➔ | Hears you calling CQ or QRZ and gets ready. |
| Copy his call sign and type it into CALL box. | ← | Sends his call sign |
| TAB to send the F2 RUN message. Send his call sign [\$] and your exchange | ➔ | Copies and enters your exchange into his log |
| SPACE BAR to advance your cursor. Copy and type his exchange into your log. | ← | Acknowledge [R] and sends his exchange |
| ENTER to send the F3 RUN message. Acknowledge [R], log the QSO, QRZ [call] TEST. You stay on frequency for the next QSO cycle. | ➔ | Hear his acknowledgement, then QSY. Tune up or down the band looking for a new contact. |
| Re-start at the top of this matrix. | | |

Type CTRL + SHIFT + G (three keys all together) to activate TAB SENDS MESSAGE feature.

Function Buttons Setup – RUN Mode:

- F1 CQ TEST [your call sign] TEST
- F2 \$ 5NN PA
- F3 R TU [your call sign] TEST
- F4 [your call sign] – used for repeats
- F5 TU 5NN PA – used for repeats
- F6 R TU [your call sign] – used for repeats
- F7 AGN
- F8 reserved for double sending your exchange
- F9
- F10
- F11
- F12

If or when you switch between Running and Search & Pounce you must edit your F2 and F3 buttons.